



Feature

- * Adopt standard 1U cabinet design.
- * 8-channel power sequence ON/OFF.
- * Remote control (power-on + 24V DC signal) of 8-channel power sequence ON/OFF - It is effective when the rocker switch is turned OFF. Support configuring CH1 and CH2 as controlled or uncontrolled status.
- * When the remote control is valid, the ALARM port on the rear panel is connected to achieve the cascade control of ALARM function.
- * The maximum load power of a single channel is 2200W, and the total load power of all channels is up to 6000W.
- * Input connector: high-power wire-coded power connector.
- * Output connector: multi-use power socket.
- * USB output interface, connected to LED lights.

Specification

| | |
|--------------------------------------|------------------------|
| Model | TS-820 |
| Rated output voltage | AC 220V 50Hz |
| Rated output current | 30A |
| Controllable power supply | 8 channels |
| Delay time of each action | 1S |
| Power supply | VAC, 220V 50/60Hz, 30A |
| Rated output power of single channel | 10A |
| Dimension (L×W×H) | 484×295×44mm |
| Weight | 4.2kg |